

OUTDOOR LED

EMERGENCY ESCAPE LIGHTING

GARRABRIDGE



SELF CONTAINED CONFIGURATION

CODE	POWER [W]	AUTONOMY [h]			MODE		OPTION		
ODB	3x1	1	2	3	SE	SA	PT	AT	RS

CENTRAL BATTERY CONFIGURATION

CODE	POWER [W]	SYSTEM	OPTION		
ODB	3x1	CB	CBS	ADS	ADL


FZLV SYSTEM CONFIGURATION

CODE	POWER [W]	SYSTEM
ODB	3x1	FZLV

Legend:

SE – non maintained
 SA – maintained
 AT – autotest
 RS – Rubic central monitoring
 FZLV – fixture for central battery FZLV 24 VDC
 CB – central battery
 CBS – central battery (circuit monitoring)
 ADS – central battery with address module ADS 20
 ADL – central battery with address module ADL
 ODB – fixture Outdoor LED

Photometry



ODB 3x1W (256lm)

h [m] - assembly height of the fitting	p ₁ [lx] - max under the fitting	R ₁ [m] for avg. 5lx	R ₁ ' [m] for avg. 5lx	R ₂ [m] for avg. 1lx	R ₂ ' [m] for avg. 1lx
2	22	3,7	2,6	6,2	4,9
2,2	18	3,7	2,6	6,4	5
2,4	15	3,6	2,6	6,6	5,1
2,6	12	3,5	2,6	6,9	5,2
2,8	11	3,4	2,5	7,2	5,4
3	9,3	3,2	2,4	7,4	5,5
3,2	8,1	2,9	2,3	7,7	5,8
3,4	7,1	2,5	2,1	7,9	5,7
3,6	6,3	2,1	1,9	8,1	5,7

MATERIALS: Stainless steel painted white

MOUNTING: Surface (wall)

POWER SUPPLY:

Self contained – 220÷240VAC/50÷60Hz
 Central battery – 220÷240VAC/50÷60Hz; 216VDC
 Central battery FZLV – 24 VDC

LIGHT SOURCE: 3x1W (256lm) power LED

CHARGING: Maximum 12h; energy-saving electronic impulse charger

AUTONOMY AND BATTERIES: 1h, 2h, or 3h, Ni-MH batteries

INSULATION CLASS: I

IP RATING: IP65

AMBIENT TEMPERATURE: t_a: 0°C÷40°C

OPTIONS:

SE – non maintained
 SA – maintained
 AT – autotest
 RS – RUBIC central monitoring
 FZLV – central battery FZLV 24V
 CB – central battery

ADDITIONAL INFORMATION:

LED indicator signalizes mains power supply and battery charge
 Deep discharge protection
 III class of insulation of FZLV version

